

MIXX12-D

Order no.: 1001177

PRODUCT INFORMATION

Digital audio mixer,

with Dante® interface.

- 12 analogue inputs, 6 analogue outputs (2 x main, 4 x aux)
- 4 Dante® inputs, 4 Dante® outputs
- Controllable via any standard iOS as well as Windows, version 8 or higher (not in the scope of delivery)
- With Dante® upgrade card for integrating device into any existing Dante® network
- State-of-the-art control technology possible via app
- Various settings possible
- User-friendly, intuitive operation
- Program selection and snapshot selection, locking function for safety
- Supports multi-platform control for up to 10 devices simultaneously
- Adjustable headphone output

The brand Dante® as well as the Dante® software which may have been integrated into these products are licenced by Audinate Pty Ltd.

Please note: RELACART products are distributed by MONACOR INTERNATIONAL exclusively in the following countries: Germany, Austria, Switzerland, Netherlands, Belgium, Luxembourg, Denmark, Portugal, Malta. Orders from other countries cannot be fulfilled.

Manufacturer information:
Relacart Electronics Co., Ltd.
1408 Room, B Building
Fengxing Plaza
No. 242, Tianhe Road
Tianhe District
Guangzhou, Guangdong
China
info@relacart.com

Importer:

MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages
The unit uses dangerous mains voltage. Leave servicing to skilled personnel only and do not insert anything into the air vents. Inexpert handling may result in electric shock.
Do not operate the unit and disconnect the mains plug from the socket immediately if the unit or the mains cable is visibly damaged; if a defect might have occurred after the unit was dropped or suffered a similar accident, if malfunctions occur. In any case, the unit must be repaired by skilled personnel.
The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).
Never pull the mains cable to disconnect the mains plug from the socket, always seize the plug.
If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

SPECIFICATIONS

MIXX12-D	
No. of channels	12
No. of inputs	16
Mic input	3.3 kΩ, bal. (XLR)
Line input	30 kΩ (6.3 mm jack)
Master output	600 Ω, bal. (XLR)
Headphones	yes
Frequency range	20-20,000 Hz
THD	< 0.005%

MIXX12-D

S/N ratio	93 dB(A)
Crosstalk	< 120 dB
Equalizer bass	DSP (4-band equalizer)
Equalizer midrange	DSP (4-band equalizer)
Equalizer treble	DSP (4-band equalizer)
equalizer	DSP (31-band equalizer)
Phantom power	+48 V
Power supply	˜ 110-240 V/50-60 Hz/60 W
Mains voltage	~ 110-240 V
Mains frequency	50-60 Hz
Power consumption, operation	60 W
Dimensions	448 x 132 x 191 mm
Width	448 mm
Height	132 mm
Depth	191 mm
Weight	4.12 kg
Packaging dimensions (W x H x L)	0.49 x 0.13 x 0.19 m
Gross weight	4.76 kg
Net weight	4.12 kg

MIXX12-D

Sampling rates	48 kHz
Resolution	24 Bit

MIXX12-D

EAN code	4007754426533
Net weight	4.12 kg