MPR-1

Order no.: 0212010

PRODUCT INFORMATION

1-channel microphone preamplifier,
with switchable phantom power.

- 1 microphone input, XLR, bal. or 6.3 mm jack, bal.
- Gain control: up to 50 dB max.
- Clip LED
- 30 V phantom power, can be activated as required

Manufacturer information:
MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages
The unit uses dangerous mains voltage. Leave servicing to skilled personnel only and do not insert anything into the air vents. Inexpert handling may result in electric shock.
Do not operate the unit and disconnect the mains plug from the socket immediately if the unit or the mains cable is visibly damaged; if a defect might have occurred after the unit was dropped or suffered a similar accident, if malfunctions occur. In any case, the unit must be repaired by skilled personnel.
The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).
Never pull the mains cable to disconnect the mains plug from the socket, always seize the plug.
If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

SPECIFICATIONS

MPR-1

Description	microphone preamplifier
Frequency range	10-30,000 Hz
Input signal	3.5 mV (XLR, bal.)16 mV (jack, bal.)
Input impedance	10 kΩ
Output signal	1 V
Gain	50 dB (with bal. connection)44 dB (with unbal. connection)
S/N ratio	58 dB
THD	0.1%
Admiss. ambient temp.	0-40 °C
Power supply	via encl. plug-in power supply
Dimensions	113 x 92 x 40 mm
Weight	345 g
Inputs	1 x XLR, 1 x 6.3 mm jack
Outputs	1 x XLR, 1 x 6.3 mm jack

MPR-1

EAN code	4007754180114
Net weight	0.53 kg