# LTR-110

Order no.: 0210500

## PRODUCT INFORMATION

**Audio transformer 1:1/2:1 for line signals**

- Unshielded version with PCB connections
- Wideband version
- Change from unbalanced to balanced and vice versa
- Galvanic isolation to avoid/eliminate hum loops
- Various level adjustment possibilities when windings are arranged accordingly

When installing unshielded transformers into units with interference fields (e.g. power transformers), attention has to be paid to respective shielding measures.

**Manufacturer information:**
MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

## SPECIFICATIONS

| **LTR-110** | |
|---|---|
| Description | line transformer |
| Frequency range | 15-30,000 Hz |
| Input signal | 5 V |
| Input impedance | 600 Ω |
| Output impedance | 600 Ω/300 Ω |
| Transmission ratio | 1:1/2:1 |
| Dimensions | 25 x 19 x 19.5 mm |
| Weight | 28 g |

**LTR-110**

| | |
|---|---|
| Inputs | PCB connections |
| Outputs | PCB connections |

**LTR-110**

| | |
|---|---|
| EAN code | 4007754087550 |
| Net weight | 0.03 kg |