# LC-31

Order no.: 0251670

## PRODUCT INFORMATION

**2-channel 2-way line combiner,**
(4 inputs/2 outputs), e.g. for connecting 2 mixers to one amplifier.

- 1 galvanically isolated, balanced XLR input (600 Ω) with ground lift switch for each channel
- 1 balanced XLR direct input for each channel
- 1 balanced XLR output (600 Ω) for each channel
- Frequency range: 20-20,000 Hz
- Robust metal housing with very good shielding qualities, suitable for stage applications
- Dimensions: 160 x 55 x 85 mm
- Weight: 761 g

**SOUNDCHECK 07/2007**
on the FGA-102, FGA-202, LC-31, MC-31 and LSP-102:
“Every musician or sound engineer should have these little helpers in their toolbox. They impress by their unobtrusiveness. Both the robust metal housing and the functionality of these transformers allow to solve many problems on stage or in the studio at a reasonable price.”

**tools4music 06/2009**
on the LSP-102, LC-31, FGA-102, FGA-202, DIB-102
“Recommendable and fit for on-the-road applications. An attractively priced little audio aid, perfect for the 'ever accompanying' tool case.”

**Manufacturer information:**
MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

**Safety Notes and Warning Messages**
The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).

If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

## SPECIFICATIONS

**LC-31**

| | |
|---|---|
| Description | combiner |
| Frequency range | 20-20,000 Hz |
| Input impedance | 600 Ω |
| Output impedance | 600 Ω |
| Admiss. ambient temp. | 0-40 °C |
| Dimensions | 160 x 55 x 85 mm |
| Weight | 761 g |
| Inputs | 4 x XLR, bal. |
| Outputs | 2 x XLR, bal. |
| Other features | ground lift switch |

**LC-31**

| | |
|---|---|
| EAN code | 4007754197716 |
| Net weight | 0.761 kg |