MPR-6

Order no.: 0210680

PRODUCT INFORMATION

Microphone preamplifier,
for connecting up to 2 microphones to a line input of a hi-fi system, an amplifier or a mixer.

- Stereo or 2 x mono
- Wide frequency range
- Black metal case
- Supplied with plug-in power supply

Manufacturer information:
MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages
The unit uses dangerous mains voltage. Leave servicing to skilled personnel only and do not insert anything into the air vents. Inexpert handling may result in electric shock.
Do not operate the unit and disconnect the mains plug from the socket immediately if the unit or the mains cable is visibly damaged; if a defect might have occurred after the unit was dropped or suffered a similar accident, if malfunctions occur. In any case, the unit must be repaired by skilled personnel.
The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).
Never pull the mains cable to disconnect the mains plug from the socket, always seize the plug.
If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

SPECIFICATIONS

MPR-6

Description	microphone preamplifier
Frequency range	5-40,000 Hz
Input signal	2 mV/1 V output
Input impedance	10 kΩ
Output signal	max. 3.2 V/47 kΩ
Gain	53 dB
S/N ratio	63 dB
THD	0.05%
Admiss. ambient temp.	0-40 °C
Power supply	via encl. plug-in power supply
Dimensions	67 x 37 x 121 mm
Weight	215 g
Inputs	2 x 6.3mm jack
Outputs	2 x RCA

MPR-6

EAN code	4007754121001
Net weight	0.275 kg