

4Ω 8Ω 16Ω

PA-302

Order no.: 0171270

PRODUCT INFORMATION

Mono PA mixing amplifier,
14 W.

- 1 microphone input and 1 line input, adjustable
- 2 speaker outputs, switchable
- Built-in speaker
- Can also be operated as an intercom system
- Supplied with hand-held push-to-talk microphone
- Siren and fog horn, automatic fog horn
- Metal housing
- Supplied with mounting brackets
- 12/24 V battery operation, automatic switching

Manufacturer information:
MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages

The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).

If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

SPECIFICATIONS

PA-302	
Peak output power	20 W
Power rating	14 W
Power rating at 4 Ω	14 W
Channels	2
Inputs	3 mV (mic), 50 mV (line)
Frequency range	20-20,000 Hz
S/N ratio	65 dB
THD	< 0.5%
Power supply	DC 12-15 V/2 A, DC 24 V/1 A
Admiss. ambient temp.	0-40 °C
Width	175 mm
Height	60 mm
Depth	170 mm
Weight	1.4 kg
Connections	1 x 6.3 mm jack (mic input), 1 x RCA (line input), 2 x 2-pole plug-in screw terminal (speakers), 1 x 3-pole plug-in screw terminal with jumper (external speakers)
Packaging dimensions (W x H x L)	0.23 x 0.1 x 0.3 m
Gross weight	1.84 kg
Net weight	1.41 kg

PA-302	
EAN code	4007754176117
Net weight	1.41 kg