

Exclusive FOR CERTIFIED PARTNERS

PA-M1WP

Order no.: 0179300

PRODUCT INFORMATION

Wall module,
for local insertion of audio signals to PA matrix mixing amplifier PA-M224 or PA-M412.

- Intended use: Volume control for the respective zone, local input of audio signals
- 2 RCA sockets for line signals
- Microphone connection via 3-pin XLR socket
- 14 V phantom power
- Adjustable volume
- Signal selection button with indicator LED, enabling priority routing of locally fed audio signals (MIC or LINE) in the respective zone
- Connection to the PA-M224 or PA-M412 and power supply via an RJ45 socket and Cat 5 network cable (copper; cable not supplied), for cable lengths up to 200 m

Manufacturer information:
MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety and warning notices

Only use the device indoors and protect it from dripping and splashing water, high humidity and heat (permissible operating temperature range 0 - 40 °C).

Do not operate the appliance if there is visible damage to the appliance, if a defect is suspected after a fall or similar, or if malfunctions occur. Always return the appliance to a specialised workshop for repair.

If the appliance is to be taken out of service permanently, hand it over to a local recycling centre for environmentally friendly disposal.

SPECIFICATIONS

PA-M1WP	
Description	wall module
Type	remote control of 1 zone
Colour	white
Material	plastic
Suitable for	PA-M224, PA-M412
Power supply	via PA-M224, PA-M412
Dimensions	80 x 80 x 50 mm
Weight	90 g
Connections	1 x XLR (microphone), 1 x RCA L/R (line), 1 x RJ45
Other features	14 V phantom power
Packing unit	1
Packaging dimensions (W x H x L)	0.09 x 0.09 x 0.085 m
Gross weight	0.135 kg
Net weight	0.09 kg

PA-M1WP	
EAN code	4007754273380
Net weight	0.09 kg