

PS-510M

Order no.: 0236720

PRODUCT INFORMATION

Phantom power supply adapter/mixer, battery-operated

- For supplying power to two microphones with 4-pole mini XLR plug (e.g. CX...W series, headband microphones and lavalier microphones of the CX/CM series)
- Allows operation at mixers, home recorders or similar devices without integrated +48 V phantom power
- Separate volume controls for the two microphones
- Adjustable headphone output
- Mute switch
- Belt clip

Manufacturer information:
JTS PROFESSIONAL CO., LTD.
No. 148, Gongye 9th Rd., Dali Dist.
41280 Taichung City
Taiwan
jts@jts.com.tw

EU-Representative:

MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages
The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).
Remove the rechargeable batteries or batteries if the device is not in use for a longer period of time (e.g. more than a week). This avoids possible damage through leaking batteries.
If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.
Batteries and rechargeable batteries must not be disposed of with household waste. They must be disposed of in accordance with local regulations for hazardous waste.

SPECIFICATIONS

PS-510M	
Category	phantom power supply adapter/mixer
Input voltage	9 V battery (not supplied)or 12-48 V phantom power
Connections	2 x 4-pole mini XLR (input)1 x XLR, bal. (output)1 x 3.5 mm jack (headphones)
Admiss. ambient temp.	0-40 °C
Dimensions	65 x 92 x 30 mm
Weight	80 g

PS-510M	
EAN code	4007754254488
Net weight	0.08 kg