

TXA-1822MR

Order no.: 0179090

PRODUCT INFORMATION

2-channel multifrequency receiver module,
with UHF PLL technology.
For retrofitting amplifier systems of the TXA-10xx and TXA-8xx series or for setting up wireless audio transmission paths.

- 2 x 16 selectable UHF frequencies (863-865 MHz)
- Volume control
- LCD for indicating selected channel and carrier frequency
- Scan function for free channel
- Supplied with adapter board for TXA-1020 and TXA-800 series

Licence-free in the EU.

Manufacturer information:
MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages

The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).

If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

SPECIFICATIONS

TXA-1822MR

General information

Description	multifrequency receiver module
Carrier frequency range	863-865 MHz
Channels	2
Admiss. ambient temp.	0-40 °C

Specifications receiver

Power supply receiver	DC 12 V/185 mA
Width receiver	88 mm
Height receiver	37 mm
Depth receiver	103 mm
Weight receiver	92 g

TXA-1822MR

EAN code	4007754269598
Net weight	0.09 kg