TXA-802PS

Order no.: 0255860

PRODUCT INFORMATION

PWM quick-charge station,
for simultaneously charging the rechargeable batteries (NC, NiMH) of one multifrequency pocket transmitter TXA-800HSE or the receiver TXA-800R and one hand-held microphone with multifrequency transmitter TXA-800HT.

- Average charging time, depending on capacity and condition of the rechargeable batteries used: approx. 4-5 hours, e.g. for 1,600 mAh rech. batteries
- Each slot with LED for indicating battery charging status
- Supplied with plug-in PSU

Manufacturer information:
MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages
The unit uses dangerous mains voltage. Leave servicing to skilled personnel only and do not insert anything into the air vents. Inexpert handling may result in electric shock.
Do not operate the unit and disconnect the mains plug from the socket immediately if the unit or the mains cable is visibly damaged; if a defect might have occurred after the unit was dropped or suffered a similar accident, if malfunctions occur. In any case, the unit must be repaired by skilled personnel.
The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).
Never pull the mains cable to disconnect the mains plug from the socket, always seize the plug.
If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

SPECIFICATIONS

TXA-802PS

Description	quick charging station
Nominal value	2 devices
Type	PWM
Colour	black
Suitable for	TXA-800HSE or TXA-800R and TXA-800HT
Power supply	via encl. power supply
Admiss. ambient temp.	0-40 °C
Dimensions	84 x 90 x 106 mm
Weight	200 g
Packing unit	1
Packaging dimensions (W x H x L)	0.095 x 0.105 x 0.17 m
Gross weight	0.37 kg
Net weight	0.29 kg

TXA-802PS

EAN code	4007754243550
Net weight	0.29 kg